

# Stainless Steel Push-in Tube Fittings Metric

4 - 12 mm O/D tube

- Resistant to aggresive environment
- Suitable for food applications
- Very compact
- Easy tube insertion and removal
- Compatible with range of tubing
- Full bore, no flow restrictions

#### **Technical Data**

Medium:

Compressed air or water

Operating Pressure: Vacuum – 18 bar

Vacuum: = -750mm of Hg i.e. 98%

Operating Temperature:

Air: -20°C to +110°C Water: 0°C to +110°C

**Tube Sizes** 

4, 6, 8, 10 and 12 mm O/D

**Tubing Types:** 

Nylon 11 or 12, Polyurethane and PTFE

#### **Materials**


Stainless steel 316 for body Stainless steel 316 for grab ring Acetal for release sleeve Viton 'O' Ring



#### **Ordering Information**

To order, quote appropriate product number from the tables on the following pages.

Product numbering system is designed to make identification and selection simple:






STRAIGHT	nectors and Ad	STRAIGHT ADAPTOR				
CONNECTOR tube to tube	BSP taper	BSP taper				
\$0020	S0125	S0225				
Page 0.0.000.03	Page 0.0.000.03	Page 0.0.000.03				
Elbow Conne	ctors, Adaptor	s and Banjos				
LBOW	ELBOW ADAPTOR BSP taper					
CONNECTOR tube to tube						
\$0040	\$0145					
Page 0.0.000.03	Page 0.0.000.03					
		ind Banjos, 'Y'			-way Connecto	ors
TEE CONNECTOR tube x 3	TEE ADAPTOR BSP taper	STRAIGHT STEM ADAPTOR	UNEQUAL STEM	BULKHEAD CONNECTOR O/D tube to O/D tube		
S0060		S0215	\$0023	S0029		
S0060	\$0165	S0215	\$0023	S0029		
	\$0165 Page 0.0.000.04	<del></del> ₽n	\$0023 Page 0.0.000.04	\$0029 Page 0.0.000.04		
Page 0.0.000.04	Page 0.0.000.04					
Page 0.0.000.04	Page 0.0.000.04					
Page 0.0.000.04	Page 0.0.000.04					
Page 0.0.000.04  Banjo Bodies	Page 0.0.000.04					
Page 0.0.000.04	Page 0.0.000.04					
Page 0.0.000.04	Page 0.0.000.04					
Page 0.0.000.04  Banjo Bodies	Page 0.0.000.04					
Page 0.0.000.04  Banjo Bodies	Page 0.0.000.04					
Page 0.0.000.04	Page 0.0.000.04					
Page 0.0.000.04  Banjo Bodies	Page 0.0.000.04					
Page 0.0.000.04  Banjo Bodies	Page 0.0.000.04					



#### **Straight Connector**

O/D tube to O/D tube




## **S0020**

Product number	A O/D tube	В	C
S00200400	4	26,0	10,0
S00200600	6	28,0	12,0
S00200800	8	33,0	15,0
S00201000	10	35,6	18,0
S00201200	12	40,8	20,0

#### **Straight Adaptor**

O/D tube to male taper BSP thread




#### S0125

Product number	A O/D tube	B thread	C	D A/F	G A/F
S01250418	4	1/8	20,5	10,0	8,0
S01250618	6	1/8	21,3	12,0	8,0
S01250628	6	1/4	23,3	14,0	10,0
S01250818	8	1/8	24,0	15,0	10,0
S01250828	8	1/4	25,8	15,0	10,0
S01251028	10	1/4	27,8	19,0	10,0
S01251038	10	3/8	29,0	19,0	11,0
S01251228	12	1/4	31,0	22,0	10,0
S01251238	12	3/8	31,5	22,0	10,0

#### **Straight Adaptor**

O/D tube to male BSPP thread




## S0225

Product number	A O/D tube	B thread	C	D A/F
S02250418	4	1/8	18,1	14,0
S02250618	6	1/8	19,0	14,0
S02250628	6	1/4	19,8	17,0
S02250818	8	1/8	24,5	15,0
S02250828	8	1/4	22,0	17,0
S02251028	10	1/4	25,3	19,0
S02251038	10	3/8	23,3	22,0
S02251228	12	1/4	27,4	22,0
S02251238	12	3/8	28,0	22,0

#### **Elbow Connector**

O/D tube to O/D tube




## **S0040**

Product	Α	C	D	E
number	O/D tube		A/F	
S00400400	4	10,9	12,0	21,5
S00400600	6	11,9	12,0	22,1
S00400800	8	15,0	12,0	25,2
S00401000	10	17,4	14,0	25,5
S00401200	12	20,0	17,0	28,5

## **Fixed Elbow Adaptor**

O/D tube to male taper BSP thread




## S0145

B D thread A/F Product G A O/D number tube BSP S01450418 12,0 | 19,0 | 21,5 | 8,0 S01450618 12,0 19,0 22,1 6 8.0 S01450628 12,0 20,5 22,1 10,0 12.0 21.5 25.2 8.0 S01450818 8 S01450828 8 1/4 12,0 21,5 25,2 10,0 S01451028 10 1/4 14,0 23,5 25,5 10,0 S01451228 12 17,0 23,0 28,5 10,0 S01451238 12 17,0 25,0 28,5 11,0

#### **Tee Connector**

O/D tube to O/D tube



## **S0060**

Product number	A O/D tube	C	D A/F	E	F
S00600400	4	43,0	12,0	21,5	10,9
S00600600	6	44,2	12,0	22,1	11,9
S00600800	8	50,4	12,0	25,2	15,0
S00601000	10	51,0	14,0	25,5	17,4
S00601200	12	57,0	17,0	28,5	20,0


#### **Fixed Tee Adaptor**

### S0165


#### O/D tube stem to male BSPP thread

**Straight Stem Adaptor** 

O/D tube to male taper BSP thread



Product number	A O/D tube	B thread BSP	C	D	E	G
S01650418	4	1/8	43,0	12,0	19,0	8,0
S01650618	6	1/8	44,2	12,0	19,0	8,0
S01650628	6	1/4	45,0	12,0	20,5	10,0
S01650818	8	1/8	50,4	12,0	21,5	8,0
S01650828	8	1/4	50,4	12,0	21,5	10,0
S01651028	10	1/4	55,0	14,0	23,5	10,0
S01651228	12	1/4	57,0	17,0	23,0	10,0
S01651238	12	3/8	57,0	17,0	25,0	11,0



Product number	A O/D tube	B thread BSP	C	D A/F
S02150418	4	1/8	25,5	14,0
S02150618	6	1/8	27,0	14,0
S02150828	8	1/4	31,0	17,0
S02151028	10	1/4	34,0	17,0
S02151238	12	3/8	36,5	22,0
S02151248	12	1/2	41,5	27,0


S0215

## **Unequal Stem**


## S0023

#### **S0029 Bulkhead Connector**

O/D tube stem to O/D tube



Product	A1	A	В	C
number	0/D stem	O/D tube		
S00230604	6	4	29,2	10
S00230804	8	4	32,2	10
S00230806	8	6	33,1	12
S00231006	10	6	35,9	12
S00231008	10	8	38,3	15
S00231206	12	6	36,3	12
S00231208	12	8	40,3	15
S00231210	12	10	45,0	18



O/D tube to O/D tube

Product number	A O/D tube	В	C A/F	E	F
S00290400	4	28,7	14,0	M11	0-6
S00290500	5	29,2	15,0	M12	0-6
S00290600	6	31,6	16,0	M13	0 - 8
S00290800	8	36,5	19,0	M16	0 - 8
S00291000	10	41,6	22,0	M19	0 - 11
S00291200	12	48,0	26,0	M22	0 - 15

#### Warning

These products are intended for use in industrial compressed air systems only. Do not use these products where pressures and temperatures can exceed those listed under 'Technical Data'.

Before using these products with fluids other than those specified, for non-industrial applications, life-support systems, or other applications not

within published specifications, consult Norgren.

Through misuse, age, or malfunction, components used in fluid power systems can fail in various modes. The system designer is warned to consider the failure modes of all component parts used in fluid power systems and to provide adequate safeguards to prevent personal injury or damage to equipment in the event of such failure.

System designers must provide a warning to end users in the system instructional manual if protection against a failure mode cannot be adequately provided.

System designers and end users are cautioned to review specific warnings found in instruction sheets packed and shipped with these products where applicable.